




SCHEMATIC # MOSI-00550-A003

REVISIONS

REVISIONS	DATE	NAME
FIRST FINISHED	11-4-81	M. KOSKIP

NOTES: 1. * = 18 AWG.
2. * = 18 AWG 500V INSUL.

POWER SUPPLY BD.
P.C.# A084-90414-C935

CPU BD.
P.C.# A084-91404-B508

FILTER BD.
P.C.# A084-91408-A508

VIDEO BD.
P.C.# A084-91405-B508


RAPID FIRE BD.
P.C.# A084-91410-A000

BOSCONIAN U.R.





DESIGNATION	DESCRIPTION
C1	10000 MF 35V AX. ELEC.
C2	.01MF 50V AX. CER.
C3	1MF 25V TANT.
C4	20000MF 16V AX. ELEC.
C5	100PF 50V AX. CER.
C6	470 MF 16V AX. ELEC.
C7	4700 MF 25V " "
R1	470 OHM 1/4W 5% CRBN
R2	100 " " " "
R3	2.7K " " " "
R4	560 " " " "
R5	510 " " " "
R6	10 " " " "
VR1	100 OHM 1/4W CRBN. FLM.
D1, D2	A14F
D3	IN4004
D4, D5	MR750
D6-D9	A15F
D10	A14F
Q1	TIP31
Q2	2N3055
U1	LM317
U2	3532
L1	FERROXCUBE BEAD
HS1	HEAT SINK
F1	FUSE 2A
F2	" 8A
F3	" 6A
FC1A, FC1B, FC2A, FC2B, FC3A, FC3B	FUSECLIP W/ STOP
J1	CONN. KK.156 (RA)(5-PIN) (6-PIN)
J2	" " (RA)(5-PIN) (13-PIN)
MHQ1	MOUNTING HARDWARE Q1 (1) SCREW 4-40X10 SLT RND (1) WSH.4 120-.250-018 (1) HEXNUT 4-40 (1) SHOULDER WSH. 974-302 THERMAL COMPOUND AS REQ. (1) TO-220 INSULATOR RT-3.5 MICA
MHQ2	MOUNTING HARDWARE Q2 (2) SCREW 4-40X10 SLT RND (2) WSH.4 120-.250-018 (2) HEXNUT 4-40 (2) SHOULDER WSH. 974-302 THERMAL COMPOUND AS REQ. (1) TO-3 RT-1.5 FILM
MHU1	MOUNTING HARDWARE U1 (1) SCREW 4-40X10 SLT RND (1) WSH.4 120-.250-018 (1) HEXNUT 4-40 (1) SHOULDER WSH. 974-302 THERMAL COMPOUND AS REQ. (1) TO-220 INSULATOR RT-3.5 MICA
TW1-TW3	TIE WRAPS




DESCRIPTION	QTY	DESIGNATION	PART NUMBER
100 PF 50v AX. CER.	1	C5	0508-00800-2100
.01MF " " "	1	C2	0171-097H2-JXXX
1MF 25v TANT.	1	C3	0935-00814-0100
470MF " AX. ELEC.	1	C6	0175-271EX-EXXX
4700MF " " "	1	C7	0508-00800-2200
10000MF 35v AX. ELEC.	1	C1	0175-322GX-EXBX
20000 16v MF " "	1	C4	0935-00814-0800
10 OHM 1/4w 5% CBN	1	R6	0062-051B3-1XXX
100 " " " "	1	R2	0062-110B3-1XXX
470 " " " "	1	R1	0062-156B3-1XXX
510 " " " "	1	R5	0062-159B3-1XXX
560 " " " "	1	R4	0062-162B3-1XXX
2.7K " " " "	1	R3	0062-199B3-1XXX
100 " " CBN FLM	1	VR1	0063-025AX-1DEX
1N4004	1	D3	0508-00801-0200
A14F	3	D1, D2, D10	0064-168XX-XXGX
A15F	4	D6-D9	0064-169XX-XXGX
MR750	2	D4, D5	0064-303XX-XXJX
TIP31	1	Q1	0065-485XX-XXXX
2N3055	1	Q2	0935-00800-0000
3532	1	U2	0066-044BX-XXXX
LM317	1	U1	0935-00804-3600
FERROXCUBE BEAD	1	L1	0017-00009-0225
HEAT SINK	1	HS1	0068-045XX-ABDX
FUSE 2A	1	F1	0017-00003-0005
FUSE 6A	1	F3	0017-00003-0008
FUSE 8A	1	F2	0017-00003-0184
FUSECLIP	6	FC1A, FC1B, FC2A, FC2B, FC3A, FC3B	0017-00003-0214
KK 156 (RA) (5)	2	J1, J2	3000-16387-0500
KK 156 (RA) (6)	1	J1	3000-16387-0600
KK 156 (RA) (13)	1	J2	3000-16387-1300
SCREW 4-40x10	4	MHU1, MHQ1, MHQ2	0017-00101-0727
WSH 4 120-.250-018	4	" " "	0017-00104-0071
HEXNUT 4-40	4	" " "	0017-00103-0002
SHOULDER WSH	4	" " "	0017-00042-0109
THERMAL COMPOUND	AS REQ.	" " "	0017-00009-0204
TO-220, INSULATOR	2	MHU1, MHQ1	0017-00003-0205
TO-3 INSULATOR	1	MHQ2	0017-00042-0108
TIE WRAPS	3	TW1-TW3	0017-00042-0105
PCB	1		A080-90414-C935

DIM. TOLERANCES UNLESS OTHERWISE SPEC. CONCENTRICITY T1 R .002 FRACTIONAL ± 1/64 DECIMAL ± .005 HOLE DIA ± .002 - .000 ANGLE ± 1/2° DO NOT SCALE DWG		FIRST USED ON: RALLY-X DATE: 2/9/82 SCALE: 1:1 MAY: 2/9/82 REVISED: 2/9/82 BY: J.S.		THIS DWG IS CONFIDENTIAL & PROPERTY OF MIDWAY MFG CO.	
MIDWAY MFG. CO. FRANKLIN PK., IL 60131 A BALLY CO.		ASSEMBLY DRWG PWR. SUPP. A084-90414-C935		PART NO M051-00935-C028	
REVISIONS					

DESIGNATION LIST

DESIGNATION	DESCRIPTION
C1, C2	.1MF 100V MYLAR
C3-C7	.01MF 25V AX CER
R1-R4	1MEG OHM 1/4w 5% CRBN RES
R5	1K " " " " "
R6	68 " " " " "
R7	1K " " " " "
R8	68 " " " " "
U1	LM556
U2	7400
J1, J2	KK.156 VERT 2(6-PIN) 2(2-PIN)
MH1-MH4	SNAP BUSHING 1/4"



CROSS REFERENCE LIST


DESCRIPTION	QUANTITY	DESIGNATION	PART #
.01MF 25VAX CER	5	C3-C7	0508-00800-0800
.1MF 100V 10% MYLAR	2	C1, C2	0508-00800-2300
68 OHM 1/4w 5% CRBN RES.	2	R6, R8	0062-09883-1XXX
1K " " " " "	2	R5, R7	0062-17983-1XXX
1MEG " " " " "	4	R1-R4	0062-32383-1XXX
LM556	1	U1	0508-00803-5500
7400	1	U2	0508-00803-5600
KK.156 CON. (2-PIN)	2	J1, J2	3000-16335-0200
(6-PIN)	2	J1, J2	3000-16335-0600
MOUNTING HARDWARE			
SNAP BUSHING 1/4"	4	MH1-MH4	0017-00042-0014
RAPID FIRE P.C	1	A080-91410-A000	A080-91410-A000

PROJECT ENG: JERRY SZERSZEN

THIS DWG IS CONFIDENTIAL & PROPERTY OF MIDWAY MFG. CO.




DIM. TOLERANCES UNLESS OTHERWISE SPEC CONCENTRICITY TIR .002 FRACTIONAL ± 1/64 DECIMAL ± .005 HOLE DIA + .002-- .000 ANGLE ± 1/2° DO NOT SCALE DWG		DATE 09-30-81 FULL		MIDWAY MFG. CO. FRANKLIN PK., IL. 60131 A BALLY CO.	
GALAGA MECH CHK DATE 09-30-81 FULL				RAPID FIRE P.C. ASSEMBLY DRAWING A082-91410-A000	
REVISIONS				PART NO. M051-00114-A001	

DESIGNATION	DESCRIPTION	DESIGNATION	DESCRIPTION
C1	470 MF ELEC.	D1	IN914B
C2-C17	.01 MF CER.	Q1	2N3391A
C18	.1MF "	Q2	2N4403
C19	.01 MF "	Q3,Q4	NOT USED
C20	22 MF ELEC.	Q5	TIP 110
C21	220 MF "		
C22	100 MF "		
C23,C24	.15 MF TANT.	IC 1A	74LS107
C25	10 MF ELEC.	" 1B	74LS285
C26-C29	.01 MF POLY.	" 1C	74LS174
C30,C31	.001 MF "	" 1D	74LS267
C32-C42	NOT USED	" 1E,1F,1H,1J,1K,1L,1M,1N	74LS139
C43	.0022 MF CER.	" 1P	74LS139
C44	10 MF ELEC.	" 2A,2B	74LS139
C45	100 PF CER.	" 2C	74LS139
C46-C48	.1 MF "	" 2D	74LS139
C49	NOT USED	" 2E,2H,2J	08XX CUSTOM IC
CX1	100 PF CER.	" 2L	06XX
CX2		" 2M	74LS246
		" 2N	8740C RAM 2K X 8
R1,R2	330 OHM 1/4w 5% CRBN.	" 2P	74LS139
R3,R4	NOT USED	" 2Q	4066 CMOS
R5	100 OHM 1/4w 5% CRBN.	" 2R	74LS273
R6	1K "	" 2S	NOT USED
R7,R8	10K "	" 2T	EPROM 8K-8
R9	NOT USED	" 2U	" 8K-8
R10	10K OHM 1/4w 5% CRBN.	" 2V	" 8K-8
R11	22K "	" 2W	" 8K-8
R12	47K "	" 2X	" 8K-8
R13	100K "	" 2Y	" 8K-8
R14	NOT USED	" 2Z	" 8K-8
R15	470 OHM 1/4w 5% CRBN.	" 3A	74LS139
R16	1K "	" 3B	74LS139
R17	2.2K "	" 3C	74LS139
R18	4.7K "	" 3D	07XX CUSTOM IC
R19	10K "	" 3E	2-80A
R20	33K "	" 3F	81XX CUSTOM IC
R21	33K "	" 3G	2-80A
R22	220K "	" 3H	74LS151
R23	100K "	" 3J	NOT USED
R24	4.7K "	" 3K	2-80A
R25	10K "	" 3L	74LS139
R26	10K "	" 3M	74LS139
R27	22K "	" 3N	74LS139
R28	47K "	" 3P	74LS139
R29	47K "	" 3Q	74LS139
R30	10K "	" 3R	74LS139
R31	22K "	" 3S	74LS139
R32,R33	47K "	" 3T	74LS139
R34	10K "	" 3U	74LS139
R35	100K "	" 3V	74LS139
R36	33K "	" 3W	74LS139
R37	10K "	" 3X	74LS139
R38	33K "	" 3Y	74LS139
R39	2.2K "	" 3Z	74LS139
R40	470K "	" 4A	80XX CUSTOM IC
R41	22K "	" 4B	84XX "
R42	150K "	" 4C	MB3730
R43	10K "	" 4D	
R44	4.7K "	" 4E	
R45	22K "	" 4F	
R46	47K "	" 4G	
R47,R48	470 "	" 4H	
R49,R50	NOT USED	" 4J,4M	
R51	10K OHM 1/4w 5% CRBN.	" 4A	
R52-R54	1K "	" 4B	
R55	10K "	" 4C	
R56-R58	1K "	" 4D	
R59,R64	NOT USED	" 4E	
R65	4.7K OHM 1/4w 5% CRBN.	" 4F	
RX1	1K "	" 4G	
		" 4H	
RM1-RM3	1K OHM 5 PIN SIP.	IC 10	16 PIN SOCKET
RM4	1K " 5 PIN "	" 2E,2H,2J,2L	28 PIN "
RM5	1K " 5 PIN "	" 2N,2E,2H,2J,2K,2L,2M,2N	34 PIN "
RM6,RM7	1K " 5 PIN "	" 4D	28 PIN "
RM8	NOT USED	" 4E	40 PIN "
RM9	1K OHM 5 PIN SIP.	" 4H	42 PIN "
RM10-RM13	2.2K " 5 PIN "	" 4J,4M	40 PIN "
RM14,RM15	NOT USED	" 5A	16 PIN "
RM16	220 OHM 5 PIN SIP.	" 5B	14 PIN "
RM17-RM20	2.2K " 5 PIN "	" 5C	16 PIN "
RM21,RM22	4.7K " " "	" 5L,5M	28 PIN "
VR1	1K POT	XTAL1	16.352 MHZ CRYSTAL
		SW1	AKC-8 P8 SWITCH
		DIP SW 6J,6K	8 POS. DIP SWITCH
		J1	CONN. R.A.HEADER 50 PIN
		J2	CONN. PCB.HEADER 3 PIN
		MMCTC	CONN. R.A.HEADER 50 PIN
			— (2) 4-40 NEX NUT
			— (2) 4-40 X 8 BLT PAN M.B.
			— (2) WSH 4 .125-250-032 FLT. ST
			— (2) WSH 4 .120-250-018 EXT. ST
		P.C.B.	BOSCONIAN CPU BD.








DESCRIPTION	QUAN	DESIGNATION	PART NO.	DESCRIPTION	QUAN	DESIGNATION	PART NO.
100 PF CER.	2	C45,C42	0550-00800-0900	PROM BS-1	1	IC 1D	0550-00803-3100
.001 MF POLY.	2	C30,C31	0550-00800-1100	" BS-2	1	" 1C	0550-00803-3200
.0022 MF CER.	1	C43	0550-00800-0800	EPROM BS-A	1	" 3N	0550-00803-3400
.01 MF "	17	C2-C17,C19	0550-00800-0700	" BS-B	1	" 3M	0550-00803-3500
.01 MF POLY.	4	C28-C29	0550-00800-1000	" BS-C	1	" 3L	0550-00803-3600
.1 MF CER.	10	C18,C46-C48	0550-00800-0600	" BS-D	1	" 3K	0550-00803-3700
.15 MF TANT.	2	C23,C24	0550-00800-1200	" BS-E	1	" 3J	0550-00803-3800
10 MF ELEC.	2	C25,C44	0550-00800-1700	" BS-F	1	" 3H	0550-00803-3900
22 MF "	1	C20	0550-00800-1800	" BS-G	1	" 3E	0550-00803-4000
100 MF "	1	C22	0550-00800-1500	STATIC RAM 2K X 8	1	" 2N	0550-00803-1000
220 MF "	1	C21	0550-00800-1400	Z-80A	3	" 4E,4J,4M	0550-00803-2200
470 MF "	1	C1	0550-00800-1300				
				14 PIN SOCKET	1	IC 8B	0550-00804-0800
100 OHM 1/4w 5% CRBN	1	R5	0082-110B3-1XXX	" " "	3	" 1D,6A,6C	0550-00804-0700
330 "	2	R1,R2	0082-144B3-1XXX	" " "	8	" 2H,2E,2H,2J,2K,2L,2M,2N	0550-00804-0400
470 "	3	R15,R47,R48	0082-156B3-1XXX	" " "	7	" 2E,2H,2J,2L,4D,6L,6M	0550-00804-0300
1K "	13	R6,R16,R52-R54,R56-R58	0082-179B3-1XXX	" " "	3	" 4E,4J,4M	0550-00804-0800
				" " "	42	" " "	0550-00804-0700
2.2K "	2	R17,R39	0082-193B3-1XXX				
3.3K "	2	R20,R38	0082-203B3-1XXX	18.432 MHZ CRYSTAL	1	XTAL1	0550-00804-1100
4.7K "	5	R19,R25,R29,R43,R65	0082-211B3-1XXX	AKC-8 P8 SWITCH	1	SW1	0550-00804-1200
10K "	11	R7,R8,R10,R19,R26,R30,R34	0082-227B3-1XXX	8 POS. DIP SWITCH	2	DIPSW1,DIPSW2	0550-00804-1400
				CONN. R.A.HEADER 50PIN	1	J1	0550-00804-0900
22K "	2	R11,R22,R27,R31,R41,R45	0082-243B3-1XXX	CONN. PCB.HEADER 3 PIN	1	J2	0017-00081-0448
33K "	8	R21,R36	0082-251B3-1XXX				
47K "	2	R12,R28,R32,R35,R46	0082-259B3-1XXX	MOUNTING HARDWARE	2	MMCTC	0017-00103-0008
100K "	2	R13,R24	0082-275B3-1XXX	4-40 NEX NUT	2	"	0017-00101-0510
150K "	5	R30,R42	0082-283B3-1XXX	WSH 4 .125-250-032 FLT. ST	2	"	0017-00104-0015
220K "	1	R22	0082-291B3-1XXX	WSH 4 .120-250-018 EXT. ST.	2	"	0017-00104-0071
470K "	1	R40	0082-307B3-1XXX				
220 OHM 5 PIN	1	RM15	0550-00804-1800				
330 " 5 PIN	5	RM1,RM3,RM5,RM9	0550-00804-1300	BOSCONIAN CPU PC.	1		A080-91412-8550
1K " 5 PIN	3	RM4,RM6,RM7	0550-00804-1600				
2.2K " 5 PIN	4	RM10-RM13	0550-00804-1900				
2.2K " 5 PIN	4	RM17-RM20	0550-00804-1500				
4.7K " 5 PIN	2	RM21,RM22	0550-00804-1700				
1K POT	1	VR1	0550-00804-1300				
IN914B	1	Q1	0550-00801-0100				
2N3391A	1	Q1	0550-00802-0200				
2N4403	1	Q2	0550-00802-0100				
TIP110	1	Q5	0550-00802-0300				
08XX CUSTOM IC	1	IC2L	0082-0080X-KAPX				
07XX "	1	" 4D	0082-0080X-KAPX				
08XX "	3	" 2E,2H,2J	0082-0070X-KAPX				
50XX "	1	" 6L	0082-0120X-KAPX				
51XX "	1	" 4H	0082-0080X-KAPX				
54XX "	1	" 6M	0082-0080X-KAPX				
74LS32	2	" 3P,4C	0550-00803-0500				
7489	2	" 2A,2B	0550-00803-0300				
74107	1	" 5B	0550-00803-0200				
74LS107	1	" 1A	0550-00803-0800				
74128	1	" 6B	0550-00803-0400				
74LS138	2	" 1P,2P	0550-00803-0700				
74LS139	2	" 4P	0550-00803-0900				
74LS151	2	" 4B,6C	0550-00803-0600				
74LS157	1	" 4K,5K	0550-00803-1000				
74LS168	1	" 2C	0550-00803-1100				
74LS245	1	" 2D	0550-00803-1200				
74LS269	1	" 2M	0550-00803-1400				
74LS273	1	" 3C	0550-00803-1800				
74LS285	1	" 3B	0550-00803-1600				
74LS387	8	" 1B	0550-00803-1700				
74LS393	1	" 1E,1F,1H,1J,1K,1L,1M,1N	0550-00803-1800				
74LS398	1	" 5A	0550-00803-1900				
LM324	1	" 6A	0550-00803-2000				
MB3730	1	" 6P	0550-00803-0800				
4066 CMOS	1	" 7C	0082-188X-KXXK				
		" 3A	0550-00803-5300				

PROJECT ENG. J. SZERSZEN		USED ON BOSCONIAN		MIDWAY MFG. CO.	
DO NOT SCALE DIMS	DATE	SCALE	NO. RECD.	PER.	DATE
DIM TOLERANCES UNLESS SPECIFIED		FULL		BOSCONIAN CPU BD.	
FRACTIONAL DECIMALS		FRACTIONAL DECIMALS		A084-91412-8550	
HOLE DIA. HOLE DIA.		HOLE DIA. HOLE DIA.		ASSY DRWNG.	
HOLE DIA. HOLE DIA.		HOLE DIA. HOLE DIA.		M051-00550-8010	



ARTS USED ON
184-91404-C508
C.B.S.

DESIGN: JERRY SZERZEN
BOSCONIAN
FULL
BOSCONIAN CPU
A084-91402-B550
SCHEMATIC
MIDWAY MFG. CO.
MO51-00550 B011
2/9/82



DESIGNATION LIST

DESIGNATION


DESCRIPTION

C 1	470 MF ELEC.
C 4	.022 MF POLY.
C 5, C6	.0047 MF "
C 7	.001 MF 100V 10% POLY
C8, C9	.001 MF 50V 10% CER.
C10-C45	.1 MF CER.
C46	220 PF MICA
C47	.001 MF 50V 10% CER.
C48	100 PF CER.
R 1	220 OHM 1/4W 5% CRBN.
R 2	470 " " " "
R 3	220 " " " "
R 4	470 " " " "
R 5	1K " " " "
R 6	220 " " " "
R 7	470 " " " "
R 8	1K " " " "
R11	10K " " " "
R12	22K " " " "
R13	47K " " " "
R14, R15	100K " " " "
R16	22K " " " "
R17	33K " " " "
R18	47K " " " "
R19	1K " " " "
R20	100 " " " "
R21-R31	1K " " " "
R32	330 " " " "
RM1-RM4	2.2 K OHM 9 PIN SIP.
RM5, RM6	1K " " " "
RM7	470 " " " "
RM8-RM10	1K " " " "
RM11	1K " 5 PIN "
Q1, Q2	2N3391A
IC 1B	74LS259
" IC	74LS138
" ID	74LS377
" IE, IH	PHAN. RAM 2K X 8
" IJ, IK	74LS374
" IM	06XX CUSTOM IC
" IN	50XX " "
" IR	07XX " "
* 2B	RAM KIT B OPTION 1
" 2C	74LS163
" 2D	PROM BS-3
" 2E	7489
" 2F, 2H	74LS245
" 2J, 2K, 2L, 2M	74LS263
" 2N	74LS244
" 2P	74LS257
" 2R	PROM BS-4
* 3A, 3B	RAM KIT B OPTION 2
" 3C, 3D, 3E, 3F	74LS163
" 3H	74LS283
" 3J	74LS20
" 3K	74LS283
" 3L, 3M	74LS86
" 3N	74LS20
" 3P	74LS86
" 3R	74LS138
" 4A	74LS174
" 4B	74LS365
" 4C	74LS273
* 4D, 4E, 4F, 4H	RAM KIT A OPTION 2
" 4J	" " " "
" 4K	03XX CUSTOM IC
" 4L	74LS377
" 4M	PROM BS-5
" 4N	03XX CUSTOM IC
" 4P	74LS368
" 5A	PHAN. PAL BS-8
" 5B	05XX CUSTOM IC
" 5D	EPROM BS-P
" 5E	" BS-N

DESIGNATION

DESCRIPTION

IC 5F, 5H	74LS174
" 5K	NOT USED
" 5L	EPROM BS-L
" 5M	" BS-K
" 5N	" BS-J
" 5R	52XX CUSTOM IC
" 6B	PROM BS-6
" 6C, 6D	74LS194
" 6E	74LS86
" 6F, 6H	74LS157
" 6J	74LS86
" 6K	74LS175
" 6L	74LS08
" 7C	74LS157
" 7D	74LS174
" 7E	74LS00
" 7F	74LS08
" 7H	PROM BS-7
" 7J	74LS175
ICS IE	24 PIN SOCKET
" IH	" "
" IM	28 PIN "
" IN	" "
" IR	16 PIN "
" 2D	" "
" 2R	" "
" 4K	18 PIN "
" 4M	16 PIN "
" 4N	18 PIN "
" 5A	20 PIN "
" 5B	24 PIN "
" 5D	" "
" 5E	" "
" 5L	" "
" 5M	" "
" 5N	42 PIN "
" 5R	16 PIN "
" 6B	" "
" 7H	" "
PCMH1-PCMH4	DUALLOCKING SPACERS
J1	50 PIN RT. ANGLE
J2	6 PIN MNL CONN.
CABLE ASSY	AS BELOW
P1, P2	PLUG-SOCKET CONNECTOR 50-PIN
CABLE	RIBBON CABLE-.33FT 50-CONNECTOR
	28 GA. STRND. RND. CONDUCTOR
A080-91413-B550	BOSCONIAN P.C.B.




NOTES

- * NOTE: RAM KIT A WILL UTILIZE EITHER OF THE FOLLOWING OPTIONS BUT NOT BOTH;
OPTION1-(1) 2148 LOC. 4J
OR
OPTION2-(4) 2147 LOC. 4D, 4E, 4F, 4H
- ** NOTE: RAM KIT B WILL UTILIZE EITHER OF THE FOLLOWING OPTIONS BUT NOT BOTH;
OPTION1-(1) 2148 LOC. 2B
OR
OPTION2-(2) HM2511 LOC. 3A, 3B

CROSS REFERENCE LIST

DESCRIPTION	QUAN.	DESIGNATION	PART NO.
100 PF CER.	1	C48	0550-00800-0900
220 PF MICA.	1	C46	0550-00800-2000
.001 MF 100V 10% POLY.	1	C7	0550-00800-2100
.001 MF 50V 10% CER.	3	C8,C9,C47	0550-00800-2400
.0047 MF POLY.	2	C5,C6	0550-00800-2200
.022 MF "	1	C4	0550-00800-2300
.1 MF CER.	38	C10-C45	0550-00800-2500
470 MF ELEC.	1	C1	0508-00800-1500
100 OHM 1/4w 5% CRBN	1	R20	0062-11083-1XXX
220 " " " "	3	R1,R3,R6	0062-13383-1XXX
330 " " " "	1	R32	0062-14483-1XXX
470 " " " "	3	R2,R4,R7	0062-15683-1XXX
1K " " " "	14	R5,R8,R19,R21-R31	0062-17983-1XXX
10K " " " "	1	R11	0062-22783-1XXX
22K " " " "	2	R12,R18	0062-24383-1XXX
33K " " " "	1	R17	0062-25183-1XXX
47K " " " "	2	R13,R18	0062-25983-1XXX
100K " " " "	2	R14,R15	0062-27583-1XXX
470 OHM 9 PIN SIP	1	RM7	0550-00804-2400
1K " " " "	5	RM5,RM6,RM8-RM10	0550-00804-2100
1K " 5PIN "	1	RM11	0550-00804-2000
2.2K " 9PIN "	4	RM1-RM4	0550-00804-2200
2N3391A	2	Q1,Q2	0550-00802-0400
03XX CUSTOM IC	2	IC 4K,4N	0066-010CX-XAPX
05XX " "	1	" 5B	0066-004CX-XAPX
06XX " "	1	" 1M	0066-005CX-XAPX
07XX " "	1	" 1R	0066-006CX-XAPX
50XX " "	1	" 1N	0066-012CX-XAPX
52XX " "	1	" 5R	0066-013CX-XAPX
74LS00	1	IC 7E	0550-00803-3400
74LS08	2	" 6L,7F	0550-00803-3500
74LS20	2	" 3J,3N	0550-00803-3600
74LS86	5	" 3L,3M,3P,6E,6J	0550-00803-3700
7489	1	" 2E	0550-00803-3300
74LS138	2	" 1C,3R	0550-00803-3800
74LS157	3	" 6F,6H,7C	0550-00803-3900
74LS163	5	" 2C,3C,3D,3E,3F	0550-00803-7100
74LS174	4	" 4A,5F,5H,7D	0550-00803-4000
74LS175	2	" 6K,7J	0550-00803-7000
74LS194	2	" 6C,6D	0550-00803-6900
74LS244	1	" 2N	0550-00803-6800
74LS245	2	" 2F,2H	0550-00803-4100
74LS257	1	" 2P	0550-00803-4200
74LS289	1	" 1B	0550-00803-4300
74LS273	1	" 4C	0550-00803-4400
74LS283	6	" 2J,2K,2L,2M,3H,3K	0550-00803-4500
74LS365	1	" 4B	0550-00803-4600
74LS368	1	" 4P	0550-00803-4700
74LS374	2	" 1J,1K	0550-00803-6700
74LS377	2	" 1D,4L	0550-00803-4800
PROM BS-3	1	IC 2D	0550-00803-5500
" BS-4	1	" 2R	0550-00803-5600
" BS-5	1	" 4M	0550-00803-5700
" BS-6	1	" 6B	0550-00803-5800
" BS-7	1	" 7H	0550-00803-5900
PHAN. PAL BS-8	1	" 5A	0550-00803-6600
EPROM BS-J	1	" 5N	0550-00803-4900
" BS-K	1	" 5M	0550-00803-5000
" BS-L	1	" 5L	0550-00803-5100
" BS-N	1	" 5E	0550-00803-5200
" BS-P	1	" 5D	0550-00803-5300
PHAN RAM 2K X8	2	" 1E,1H	0550-00803-5400

DESCRIPTION	QUAN.	DESIGNATION	PART NO.
PHAN RAM A OPTIONS	1		0550-00803-6000
* RAM KIT A OPTIONS I	1	IC 4J	0550-00803-6200
* " " " " 2	4	" 4D,4E,4F,4H	0550-00803-6300
PHAN RAM B OPTIONS	1		0550-00803-8100
** RAM KIT B OPTIONS I	1	IC 2B	0550-00803-6400
** " " " " 2	2	" 3A,3B	0550-00803-6500
16 PIN SOCKET	5	ICS-2D,2R,4M,6B,7H	0508-00804-0700
18 PIN "	2	" 4K,4N	0508-00804-0800
20PIN "	1	" 5A	0550-00804-2300
24PIN "	8	" 1E,1H,5B,5D,5E,5L	0508-00804-0500
		" 5M,5N	
28 PIN "	3	" 1M,1N,1R	0508-00804-0400
42 PIN "	1	" 5R	0508-00804-1900
6 PIN MNL CONN.	1	J2	0017-00021-0424
50 PIN RT. ANGLE CONN.	1	J1	0508-00804-0800
DUAL LOCKING SPACERS	4	PCMHI-PCMHA	0017-00042-0253
CABLE ASSY.	1		0508-00804-2200
50-PIN PLUG-SOCKET CONNECTOR	2	P1,P2	0508-00804-0900
RIBBON CABLE-.33FT	1	CABLE	0017-00033-0346
50-CONDUCTOR 28 GA.			
STRND AND CONDUCTOR			
BOSCONIAN P.C.B	1		A080-91413-B550




PROJECT ENG: J. SEZERSZEN



USED ON BOSCONIAN

REVISIONS

DO NOT SCALE DWG	HEAT TREAT	SCALE	NO REQ'D I PER	MIDWAY MFG. CO.
DIM TOLERANCES UNLESS SPECIFIED	MAT'L	FULL		FRANKLIN PK ILL
DATE PREPARED: 1-1-82	DATE TESTED: 1-1-82	DATE REVISION: 1-1-82		PART NO.
BY: J.S.	BY: J.S.	BY: J.S.		M051-00550-B012
DATE: 2/9/82	DATE: 2/9/82	DATE: 2/9/82		BOSCONIAN VIDEO A084-91413-B550 ASS'Y DRWG.







NUMBER	DESCRIPTION	QUANTITY	DESIGNATION	PHANTOM NUMBER
00-0500	3 PIN HEADER	2	J2-J3	0017-00021-0443
00-0100	AMP 350429-1			
00-0200	6 PIN HEADER	2	J4-J5	0017-00021-0424
00-0300	AMP 350431-1			
00-0400	PC EDGE CON KEY	2	J1MH	0017-00021-0396
XX-XXAX	6-32x10 SLOT	2	J1MH	0017-00101-0574
	PAN SCREW			
04-0100	WSH 6	2	J1MH	0017-00104-0002
	145-.250-.032			
04-0200	BRKT-	1	J1MH	0866-00116-00XF
21-0418	CONN.FIN			


PROJECT ENGINEER L. LEKKER

THIS DWG. IS CONFIDENTIAL & PROPERTY OF MIDWAY MFG. CO.

DIM. TOLERANCES UNLESS OTHERWISE SPEC. CONCENTRICITY T.I.R.002 FRACTIONAL ... ± 1/64 DECIMAL ... ± .005 HOLE DIA. ... +.002-.000 ANGLE ... ± 1/2° DO NOT SCALE DWG		FIRST USED ON DRN CKS DATE 1-4-82 SCALE FULL MECH CHK _____ MAT'L _____ ELEC CHK _____ FINISH _____	MIDWAY MFG. CO. FRANKLIN PK., IL. 60131 A BALLY CO. BOSCONIAN FILTER P.C. ASSY. DRWG. A084-91414-A550	REVISIONS PART NO. M-0-5-1 - 0-0-5-5 0-A-0-1-4
--	--	---	---	---


S DATED

<u>DESIGNATION</u>	<u>DESCRIPTION</u>
C1	.1MF AX CER
C2-C5	47 PF AX CER
C6, C7	470PF AX CER
C8-C13	100PF AX CER
C14-C36	.01 MF AX CER
L1-L4	CHOKE 10UH W.W. MILLER
L5-L8	CHOKE 10UH W.W.
L9-L12	CHOKE ENCAP 10 UH
J1	P.C. EDGE CONN
J2, J3	3 PIN HEADER
J4, J5	6 PIN HEADER
J1 M.H.	2 EDGE CONN. KEY
	(2) 6-32x10 SLOT PAN SCREW
	(2) WSH 6 145-.250-.032
	(1) BRKT.-CONN. FIN.



<u>DESCRIPTION</u>	<u>QUANTITY</u>	<u>DESIGNATION</u>	<u>PHANTOM NUMBER</u>
47 PF 50V AX CER	4	C2-C5	0550-00800-0500
100PF 50V AX CER	6	C8-C13	0550-00800-0100
470PF 50V AX CER	2	C6, C7	0550-00800-0200
.01MF 50V AX CER	23	C14-C36	0550-00800-0300
.1MF 50V AX CER	1	C1	0550-00800-0400
10UH W.W. RF CHOKE MILLER	4	L1-L4	0067-021XX-XXAX
10UH W.W. RF CHOKE	4	L5-L8	0550-00804-0100
10UH ENCAP RF CHOKE	4	L9-L12	0550-00804-0200
P.C. EDGE CONN	1	J1	0017-00021-0418

PLEASE DESTROY ALL PRINTS DATED
PRIOR TO 1-4-82



NOTE:
 ALL .1+.01 ARE MF
 ALL CAPS AX. CER. UNLESS
 NOTED OTHERWISE
 * 1.5 AMP (MILLER TYPE)
 INDUCTORS

PROJECT ENG: L. DEKKER

THIS DWG. IS CONFIDENTIAL & PROPERTY OF MIDWAY MFG. CO.

DIM. TOLERANCES UNLESS OTHERWISE SPEC	DATE	BY	CHKD	APPD	REV	REVISIONS
CONCENTRICITY ± .002	12-22-80	MM			FULL	
FRACTIONAL ± .002						
DECIMAL ± .005						
HOLE DIA ± .002 - .000						
ANGLE ± 12°						
DO NOT SCALE DWG						
MIDWAY MFG. CO. FRANKLIN PK. IL 60131 A BALLY CO.						
BOSCONIAN FILTER BOARD A084-913-55						
PART NO M051-00550-A015						